XMP: Manometer for indicating measured values

Areas of application

Displaying measured values in pneumatic control equipment.

Features

- Part of the Centair family of systems
- Several versions for displaying different values and ranges
- Pressure gauges are suitable for incorporating into standard controllers in the RCP product range
- Accessories make it possible to build into various controllers or panels
- Removable Plexiglas cover for readjusting the pointer
- Connection via thread G 1/8" A or 2.3 mm ø plug nipple
- Complies with directive 97/23/EC Art. 3.3 on pressure equipment

Technical description

• Pressure gauge in accuracy class 1.6

Туре	Scale	Rough	Use	Weight	
	range	scale		kg	
XMP 020/40 F001	-2040 °C	0,21,0 bar	temperature	0,05	
XMP 5/35T F001	535 °C	0,21,0 bar	temperature	0,05	
XMP 0/120T F001	0120 °C	0,21,0 bar	temperature	0,05	
XMP 80/200 F001	80200 °C	0,21,0 bar	temperature	0,05	
XMP 20/90F F001	2090% rh	0,21,0 bar	rel. humidity	0,05	
XMP 0/20AF F002	020 g/kg	0,21,0 bar	abs. humidity	0,05	
XMP 0/5ND F001	05,0 mbar	0,21,0 bar	low pressure	0,05	
XMP 5/10ND F001	510 mbar	0,21,0 bar	low pressure	0,05	
XMP 0/100E F001	0100%	0,21,0 bar	standard signal	0,05	
XMP 0/16B F001	01,6 bar	_	output pressure	0,05	
XMP 50/50P F001	-5050 Pa ¹⁾	_	low pressure	0,05	
Accuracy	Class 1,6	Permissible ambient temp.		055 °C	
Max. operating pressure	1,4 bar				
XMP 0/16B	1,6 bar	Dimension	n drawing	M297045	

Accessories

0297044 000* Accessories for panel fitting





^{*)} Dimension drawing or wiring diagram are available under the same number

¹⁾ Pressure gauge for RLP 100 F901/F915 room-pressure controller; indication of room press. Double scale: -20...+20/-50...+50 Pa = 0,2...1,0 bar. The range can be selected by ticking one of two boxes on the scale.


Operation


A Bourdon tube is pressurised, and the pressure is converted into a change of direction which is indicated by a pointer on the scale.

Technical information

Technical manual: centair system 0304991 003

Dimension drawing





Accessories



